

# Signlab 7.1

## Metamark Profiles Installation

---

The following instructions describe how to import Metamark media profiles into the RIP. If you need any further assistance please contact the sales office on 0845 345 5645:

1. The printmode files are all named *Printer*.pmz, and can be imported by going to Print and Cut Manager > Printers > Manage Printmodes, and select your printer.
2. Then go to the far right icon (import printmode package), browse to the printmode package .pmz file and it will list all the printmodes available in the file, select the ones you need and then import and click the import button. The print modes are then added to the printmodes listing.
3. Printmodes are labelled as follows:
  - a. JV3 4 colour - MimkJV34.pmz
  - b. Roland Versacamm - RSP300.pmz

\*If a printmode for the JV3 is selected and the job errors then they will need the files and instructions. The new driver consists of two files Mimkv34.pdx which needs to be copied to C:\Cadlink\Print and Cut manager\Printers folder and Mimaki JV3 – 2xCMYK (which when e-mailed gains an extension of .DAT this should be removed) the file needs to be copied to C:\Cadlink\Print and Cut manager\rip\system\pie folder.